

Electric Towel Rails

Models : LSTS

08/52814/0 (UK) Issue 0



Intertek

Dimensions

(millimetres)




Fig. 1

IMPORTANT : THESE INSTRUCTIONS SHOULD BE READ CAREFULLY AND RETAINED FOR FUTURE REFERENCE

Important Safety Advice

Note - The following warnings are required to meet EU legislation, some areas do not apply to this product as the temperature has been limited

WARNING - THE SURFACE OF THIS RADIATOR CAN BE HOT.

In order to be effective the towel rail will get hot, however momentary contact with any part of it should not cause injury.

WARNING - In order to avoid a hazard for very young children, this appliance should be installed so that the lowest heated rail is at least 600mm above the floor.

WARNING - This appliance must not be located immediately above or below a fixed socket outlet or connection box.

IMPORTANT - If the towel rail is to be installed in a place used by the public, a warning notice should be placed adjacent to the rail advising that the surface can be hot.

CAUTION - This appliance can be used by children aged from 8 years and above and persons with reduced physical, sensory or mental capabilities or lack of experience and knowledge if they have been given supervision or instruction concerning use of the appliance in a safe way and understand the hazards involved. Children shall not play with the appliance. Cleaning and user maintenance shall not be made by children without supervision.

Children of less than 3 years should be kept away unless continuously supervised. Children aged from 3 years and less than 8 years shall only switch on/off the appliance provided that it has been placed or installed in its intended normal operating position

and they have been given supervision or instruction concerning the use of the appliance in a safe way and understand the hazards involved. Children aged from 3 years and less than 8 years shall not plug in, regulate and clean the appliance or perform user maintenance.

CAUTION - This appliance is not intended for use by children or other persons without assistance or supervision if their physical, sensory or mental capabilities prevent them from using it safely. Children should be supervised to ensure that they do not play with the appliance.

The towel rail is to be installed so that switches and other controls cannot be touched by a person in the bath or shower.

IMPORTANT - If the supply cord is damaged it must be replaced by the manufacturer or service agent or a similarly qualified person in order to avoid a hazard.

Precautions should be taken to ensure that prolonged contact with the towel rail cannot occur. Particular care should be taken in confined areas where accidental prolonged contact with the rail could be more likely to occur.

This appliance should only be used to dry fabrics washed in water using commonly available detergents.

A means for disconnection must be incorporated in the fixed wiring in accordance with the wiring rules.

General

Your Dimplex electric towel rail has been designed to provide an all-year-round service for airing towels and articles of clothing. It is not intended to provide a sole heating service.

The Dimplex LSTS is designed for wall mounting only, and is splash-proof.

Use

Your Dimplex electric towel rail can quite safely be left on continuously if desired without detrimental effect. When in use however no more than three layers of towelling or similar fabric should be draped over each rail. It is not advisable to leave very damp clothes or towels on the rail when it is not in use, as this may affect the finish.

The rail when in use, will be warm to the touch, but is not hot enough to scorch or burn towels or clothes.

The rail has been designed to meet the recommendations of the NHS guidelines on safe surface temperatures and will not exceed 43°C during normal operating conditions. This ensures the product is safe to use in sensitive environments such as nurseries, care homes and public areas.

Electrical

The electrical installation of this towel rail must be carried out by a competent electrician in accordance with the current I.E.E Regulations for Electrical Equipment. The towel rail is suitable for use on an A.C.~ electrical supply. Before installation check that the supply voltage corresponds with that marked on the rail.

WARNING - THIS APPLIANCE MUST BE EARTHED.

IMPORTANT - The wires in the mains lead are coloured in accordance with the following code:

GREEN and YELLOW - **EARTH** 
BLUE - **NEUTRAL**
BROWN - **LIVE**

In accordance with wiring rules a suitable means for disconnection must be incorporated in the fixed wiring.

If fitted in a room containing a bath or shower, to comply with the current I.E.E. Regulations, a cable outlet will be necessary with the supply to the heater controlled by a double-pole pull-cord switch having a contact separation of 3mm in each pole. The body of the switch should be situated as to be normally inaccessible to a person using a bath or shower.

Installation

The towel rail must be permanently fitted to the wall.

The rail must be so mounted that the top is at least 50mm/2" below any overhanging surface. Sufficient space must be left for access to the terminal cover screws without removing the rail from the wall.

The rail can be mounted facing left or right, with the cable entry position at the bottom.

Wall mounting




Fig. 2

The Wall mounting pack contains:

- (a) 3 mounting straps
- (b) 3 screws (M4 x 10)
- (c) 3 wall mounting brackets
- (d) 3 locator pins

Procedure for fixing Wall Brackets

Step 1

Mark the hole position (x) - see Fig. 1 - for the first fixing bracket and drill and plug the wall to suit. Fit the wall mounting bracket.

Step 2

Place the mounting strap carefully around the lower rail - see Fig. 3. Securely fix it by screwing in place fully the M4 x 10mm screw. Ensure the bracket is fitted with the rear of the strap facing directly backwards.

Step 3

Place the mounting strap into the wall mounted bracket, secure it with the locator pin by inserting it and giving it a quarter turn - see Fig. 3.

Note: Take care and hold the towel rail in position as one bracket is not sufficient to secure the towel rail to the wall.

Step 4

You now have a fixed point to help you mark the other hole positions for the other two wall mounting brackets. Remove the locator pin, and place towel rail carefully to one side to allow you to repeat Steps 1, 2 and 3, for the other brackets.




Fig. 3

To replace Cable

WARNING - The cable should only be replaced by a service agent or a similiary qualified person.

To gain access to the terminals first remove the two screws holding the cover in position. These screws are on top and underneath. Remove the screw from the bottom moulding. Remove the top cover with the neon lens and connect the wires as shown in Fig. 4 below.




Fig. 4

Cleaning

The finish on your towel rail can be maintained by occasionally wiping over with a damp cloth and lightly finishing with a soft dry cloth. This should only be carried out when the rail is cold. **Do not** use abrasive cleaning powders as this could damage the surface finish.

Recycling



For electrical products sold within the European Community. At the end of the electrical products useful life it should not be disposed of with household waste. Please recycle where facilities exist. Check with your Local Authority or retailer for recycling advice in your country.

After Sales Service

Your product is guaranteed for two years from the date of purchase. Within this period, we undertake to repair or exchange this product free of charge (subject to availability) provided it has been installed and operated in accordance with these instructions.

Your rights under this guarantee are additional to your statutory rights, which in turn are not affected by this guarantee.

Should you require after sales information or assistance with this product please go to www.dimplex.co.uk where you will find our self help guide by clicking on "After Sales" or call our helpdesk on 0844 879 3587 (UK) or 01 842 4833 (R.O.I.) .

Spare parts are also available on the website.

www.dimplex.co.uk

Please retain your receipt as proof of purchase.



The product complies with the European Safety Standards EN60335-2-43 and the European Standard Electromagnetic Compatibility (EMC) EN55014, EN60555-2 and EN60555-3. These cover the essential requirements of EEC Directives 2006/95/EC and 2004/108/EC

Dimplex UK Ltd.
Millbrook House
Grange Drive
Hedge End
Southampton
Hampshire. SO30 2DF

TEL: 0844 879 3587

FAX: 0844 879 3583

WEBSITE: www.dimplex.co.uk

Republic of Ireland

Tel.

01 8424833